



## D 62 FOX

## TECHNICAL DATASHEET D 62 FOX



### BIG FOX "FOX"



For illustrative purposes only

### ENGINE

Description	DEUTZ
Engine model	BF4M2011C
Cylinders	4
RPM speed	1800
Cubic capacity	3.11 l
Air intake	Turbocharged
Standard voltage	12 Vdc
Optional voltage	24 Vdc
Sae	3-11½
BMEP	1440 kPa
Cooling	Oil
Flywheel P.R.P. Power net	56.9 kW
Flywheel E.P. Power net	60.1 kW
Fuel Cons. at 100% (E.P.)	0.0 l/h
Fuel Cons. at 100% (P.R.P.)	16.3 l/h
Fuel Cons. at 75% (P.R.P.)	12.2 l/h
Fuel Cons. at 50% (P.R.P.)	8.3 l/h
Fuel Cons. at 25% (P.R.P.)	4.8 l/h
Electronic regulator	On request
Precision class	G2
Oil quantity	13.0 l
Engine Antifreeze capacity	0.0 l
Radiator type	TR
Heat from radiator	38.7 kW
Heat from exhaust	0.0 kW
Heat from radiation	0.0 kW
Exhaust temperature	530 °C
Portata Raffreddamento	62.3 m³/min
Combustion air flow	5.3 m³/min
Exhaust gas flow	14.9 m³/min
TA Luft	N
TA Luft/2	N
EPA	N
Stage	N

### MAIN DATA

Continuous power (PRP)	<b>63.00</b> kVA
Continuous power (PRP)	<b>50.40</b> kW
Emergency power (E.P.)	<b>66.00</b> kVA
Emergency power (E.P.)	<b>52.80</b> kW
VAC - HZ - cos(fi)	<b>208 - 60 - 0.8</b>

### DIMENSIONS AND WEIGHT

Width	945 mm
Length	2240 mm
Height	1340 mm
Weight	1080 kg

### ALTERNATOR

Description	STAMFORD
Alternator model	S1L2-Y
P.R.P. Power	66.0 kVA
E.P. Power	72.6 kVA
Connection	Parallel star
Phases	3FN
Winding	311
Terminal Number	12 nr.
IP Protection	23
Electronic regulator	AS540
Precision	1.0 ± %

### BASEFRAME

Model	FOX
Standard tank	90 l
Optional tank	0 l
Oversized tank*	0 l

### CANOPY & SILENCER

Canopy model	FOX
Silencer model	F60/00
Silencer outlet diameter	60.0 mm

Standard reference conditions temperature 25°C, altitude 100m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850kg/l. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance. **P.R.P. - Prime Power-Continuous power at variable load:** The power that a genset can supply in continuous service at a variable load for an unlimited number of hours per year while respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer. according to ISO8528-1. The average power supplied over time and any applicable overload must be less than the percentages stated by the Manufacturer. **E.P. - Emergency power:** This is the maximum power that a generating set can deliver for a limited number of hours per year while complying with the maintenance frequency stipulated under the environmental conditions set by the Manufacturer. The number of hours per year is determined by the engine manufacturer. The average power output over time must be lower than the percentages set by the engine manufacturer. Overloading is not allowed.

The data contained in this document is nominal and refers to the standard equipped model and is not binding. Visa S.p.A. reserves the right to revise the information without notice per our policy of continuous product development and improvement.

