



FOX "FOX"



For illustrative purposes only

ENGINE

Description	PERKINS
Engine model	403A-15G2
Cylinders	3
RPM speed	1800
Cubic capacity	1.50 l
Air intake	Aspirated
Standard voltage	12 Vdc
Optional voltage	Vdc
Sae	4-7½
BMEP	728 kPa
Cooling	Water
Flywheel P.R.P. Power net	16.1 kW
Flywheel E.P. Power net	17.8 kW
Fuel Cons. at 100% (E.P.)	5.1 l/h
Fuel Cons. at 100% (P.R.P.)	4.3 l/h
Fuel Cons. at 75% (P.R.P.)	3.1 l/h
Fuel Cons. at 50% (P.R.P.)	2.3 l/h
Fuel Cons. at 25% (P.R.P.)	1.6 l/h
Electronic regulator	On request
Precision class	G2
Oil quantity	6.0 l
Engine Antifreeze capacity	2.6 l
Radiator type	TR
Heat from radiator	13.7 kW
Heat from exhaust	17.2 kW
Heat from radiation	4.7 kW
Exhaust temperature	590 °C
Cooling air flow	0.0 m³/min
Combustion air flow	0.0 m³/min
Exhaust gas flow	2.6 m³/min
TA Luft	N
TA Luft/2	N
EPA	N
Stage	N

MAIN DATA

Continuous power (PRP)	17.50 kVA
Continuous power (PRP)	14.00 kW
Emergency power (E.P.)	19.50 kVA
Emergency power (E.P.)	15.60 kW
VAC - HZ - cos(fi)	208 - 60 - 0.8
Sound pressure 7 m.	67.0 dBA

DIMENSIONS AND WEIGHT

Width	770 mm
Length	1660 mm
Height	1330 mm
Weight	660 kg

ALTERNATOR

Description	STAMFORD
Alternator model	PI044H
P.R.P. Power	19.3 kVA
E.P. Power	21.2 kVA
Connection	Parallel star
Phases	3FN
Winding	311
Terminal Number	12 nr.
IP Protection	23
Electronic regulator	AS480
Precision	1.0 ± %

BASEFRAME

Model	FOX
Standard tank	50 l
Optional tank	600 l
Oversized tank*	0 l

CANOPY & SILENCER

Canopy model	FOX
Silencer model	F50/02
Silencer outlet diameter	50.0 mm

Standard reference conditions temperature 25°C, altitude 100m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850kg/l. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance. **P.R.P. - Prime Power-Continuous power at variable load:** The power that a genset can supply in continuous service at a variable load for an unlimited number of hours per year while respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer. according to ISO8528-1. The average power supplied over time and any applicable overload must be less than the percentages stated by the Manufacturer. **E.P. - Emergency power:** This is the maximum power that a generating set can deliver for a limited number of hours per year while complying with the maintenance frequency stipulated under the environmental conditions set by the Manufacturer. The number of hours per year is determined by the engine manufacturer. The average power output over time must be lower than the percentages set by the engine manufacturer. Overloading is not allowed.

The data contained in this document is nominal and refers to the standard equipped model and is not binding. Visa S.p.A. reserves the right to revise the information without notice per our policy of continuous product development and improvement.

