



## DS 300 GX



## GALAXY "GX"



For illustrative purposes only

## ENGINE

Description	HYUNDAI(DOOSAN)
Engine model	DP086CE
Cylinders	6
RPM speed	1500
Cubic capacity	7.53 l
Air intake	Turbocharged
Standard voltage	24 Vdc
Optional voltage	Vdc
Sae	1-14
BMEP	3130 kPa
Cooling	Water
Flywheel P.R.P. Power net	260.5 kW
Flywheel E.P. Power net	287.5 kW
Fuel Cons. at 100% (E.P.)	68.9 l/h
Fuel Cons. at 100% (P.R.P.)	62.3 l/h
Fuel Cons. at 75% (P.R.P.)	45.7 l/h
Fuel Cons. at 50% (P.R.P.)	30.9 l/h
Fuel Cons. at 25% (P.R.P.)	16.6 l/h
Electronic regulator	Standard
Precision class	G3
Oil quantity	35.0 l
Engine Antifreeze capacity	18.0 l
Radiator type	TE
Heat from radiator	112.0 kW
Heat from exhaust	0.0 kW
Heat from radiation	0.0 kW
Exhaust temperature	663 °C
Cooling air flow	0.0 m³/min
Combustion air flow	17.8 m³/min
Exhaust gas flow	53.7 m³/min
TA Luft	N
TA Luft/2	N
EPA	N
Stage	N

The data contained in this document is nominal and refers to the standard equipped model and is not binding. Visa S.p.A. reserves the right to revise the information without notice per our policy of continuous product development and improvement.

## MAIN DATA

Continuous power (PRP)	<b>308.00</b> kVA
Continuous power (PRP)	<b>246.40</b> kW
Emergency power (E.P.)	<b>340.00</b> kVA
Emergency power (E.P.)	<b>272.00</b> kW
VAC - HZ - cos(f <sub>i</sub> )	<b>400 - 50 - 0.8</b>
Sound pressure 7 m.	<b>71.0</b> dBA

## DIMENSIONS AND WEIGHT

Width	1350 mm
Length	4270 mm
Height	2370 mm
Weight	3380 kg

## ALTERNATOR

Description	STAMFORD
Alternator model	S4L1D-D
P.R.P. Power	310.0 kVA
E.P. Power	340.0 kVA
Connection	Series star
Phases	3FN
Winding	311
Terminal Number	12 nr.
IP Protection	23
Electronic regulator	AS440
Precision	1.0 ± %

## BASEFRAME

Model	GV121
Standard tank	500 l
Optional tank	0 l
Oversized tank*	0 l

## CANOPY &amp; SILENCER

Canopy model	GV121/00/1
Silencer model	MSR/a 100
Silencer outlet diameter	114.0 mm

Standard reference conditions temperature 25°C, altitude 100m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850kg/l. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance. **P.R.P. - Prime Power-Continuous power at variable load:** The power that a genset can supply in continuous service at a variable load for an unlimited number of hours per year while respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer, according to ISO8528-1. The average power supplied over time and any applicable overload must be less than the percentages stated by the Manufacturer. **E.P. - Emergency power:** This is the maximum power that a generating set can deliver for a limited number of hours per year while complying with the maintenance frequency stipulated under the environmental conditions set by the Manufacturer. The number of hours per year is determined by the engine manufacturer. The average power output over time must be lower than the percentages set by the engine manufacturer. Overloading is not allowed.

